



Product Information		Lepro LE	
Product conformity acc. to	:	Ecodesign requirements	
Supplier's name or trade mark	:	Lepro, LE	
Supplier's address	:	One Spencer Dock, North Wall Quay, Dublin 1, D01 X9R7, Ireland	
Model identifier	:	340014-DW-EU	
Model identifier of all equivalent models	:	340014-DW-EU	
With separate control gear	:	no	
Type of light source			
Lighting technology used	:	LED	Non-directional or directional
Mains or non-mains	:	NMLS	Connected light source (CLS)
Colour-tunable light source	:	no	Envelope
High luminance light source	:	no	Anti-glare shield
Dimmable	:	no	
General product parameters			
Energy consumption in on-mode (kWh/1000h)	:	95.0	Energy efficiency class
Useful luminous flux, indicating if it refers to the flux in a sphere, in a wide cone or in a narrow cone (lm)	:	12000	in sphere
On-mode power (P _{on}), expressed in W	:	95.0	Standby power (P _{sb}) expressed in W and rounded to the second decimal
Networked standby power (P _{net}) for CLS, expressed in W and rounded to the second decimal	:	-	Colour rendering index, rounded to the nearest integer, or the range of CRI values that can be set
Outer dimensions without separate control gear, lighting control parts and non-lighting control parts if any (mm)	:	Hight 194 Width 107.5 Depth 5	Spectral power distribution in the range 250nm to 800 nm at full-load
Claim of equivalent power	:	-	If yes, equivalent power (W)
	:	-	Chromaticity coordinates (x and y)
Parameters for directional light sources			
Peak luminous intensity (cd)	:	-	Beam angle in degrees, or the range of beam angles that can be set
Parameters for LED and OLED light sources			
R9 colour rendering index value	:	10	Survival factor
the lumen maintenance factor	:	0.96	
Parameters for LED and OLED mains light sources			
displacement factor	:	-	Colour consistency in McAdam ellipses
Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage	:	-	If yes then replacement claim (W)
Flicker metric (Pst LM)	:	-	Stroboscopic effect metric (SVM)




Declared/Measured values				
Voltage (V)	:	270VDC		Useful luminous flux (lm) : 12000 in sphere
Frequency (Hz)	:	-		Luminance-HLLS (cd/mm ²) : - HLLS
On-mode power P _{on} (W)	:	95		Beam angle (°) : - DLS
Standby power P _{sb} (W)	:	0.05		Networked standby power P _{net} (W) : - CLS
Displacement factor	:	0.95		CCT(K) : 6500
Colour consistency (SDCM)	:	5		CRI : 80
Flicker metric P _{stLM}	:	-		Stroboscopic effect metric SVM : -
P _{onmax} (W)	:	101.5		excitation purity for Blue 440nm-490nm : - CTLS
Total mains efficacy (lm/W)	:	126.3		excitation purity for Green 520nm-570nm : - CTLS
LB0750(H)	:	50000		excitation purity for Red 610nm-670nm : - CTLS
Parameters for separate control gear				
Voltage (V)	:	-		Maximum output power (W) : -
No-load power P _{no} (W)	:	-		Efficiency in full load (%) : -
Standby power P _{sb} (W)	:	-		Networked standby power P _{net} (W) : -
the type of light sources for which it is intended	:	NMLS	LED	compatible dimmable light sources : only the together light source
Outer dimensions (mm)	Height	-		mass(g) : -
	Width	-		
	Depth	-		
$\eta_{TM} = (\Phi_{use}/P_{on}) \times FTM \text{ (lm/W)} = 126.3 \text{ lm/W}$ 110 ≤ η_{TM} < 135 energy efficiency class correspond to E				
Energy efficiency and functional requirements				
Classification acc. To 2019/2020		Directional lamp		<input checked="" type="checkbox"/> Non directional lamp
Compliance:	<input checked="" type="checkbox"/>	Yes		<input type="checkbox"/> No
Measurement conditions				
Standards	:	EU 2019/2015, EU 2019/2020		
Tolerances	:	according to ErP regulation		
Measurement setup	:	4P, SSL port, 1.5m sphere		
Voltage (V)	:	declared voltage		
Burning position	:	Base up		
Ambient temperature:	:	25°C +/- 2K		
Burn in	:	1h		
Total operating time during measurement	:	15min		
Non standard stability criteria	:	Luminous flux tolerance 0.5% within 60 sec.		
Uncertainties	:	according to JCGM (GUM) and CIE 198		
Important notes / WARNINGS:				
1. This product contains replaceable light sources and separated control gears. The replaceable shall be the same model no. and brands. 2. Separate the light source and control gears from the containing products at the end of life. 3. The product needs to be powered off before install; Please see users' instruction				
Signature	:	Vick XUN		

Disassembly Instruction for removing LS and SCG


Disassembly Instruction



1




2



3




6



5




4




7



8




9



12



1



10



13



14

Explanation text size : Arial 9 Black

Flow arrow used format

