

Product Information		Lepro LE	
Product conformity acc. to	:	Ecodesign requirements	
Supplier's name or trade mark	:	Lepro	
Supplier's address	:	One Spencer Dock, North Wall Quay, Dublin 1, D01 X9R7, Ireland	
Model identifier	:	PR1500024-DW-EU	
Model identifier of all equivalent models	:	-	
With separate control gear	:	no	
Type of light source			
Lighting technology used	:	LED	Non-directional or directional
Mains or non-mains	:	MLS	Connected light source (CLS)
Colour-tunable light source	:	no	Envelope
High luminance light source	:	no	Anti-glare shield
Dimmable	:	no	
General product parameters			
Energy consumption in on-mode (kWh/1000h)	:	15.0	Energy efficiency class
Useful luminous flux, indicating if it refers to the flux in a sphere, in a wide cone or in a narrow cone (lm)	:	1450 in sphere	Correlated colour temperature, rounded to the nearest 100K, or the range of correlated colour temperatures rounded to the nearest 100K, that can be set
On-mode power (Pon), expressed in W	:	15.0	Standby power (Psb) expressed in W and rounded to the second decimal
Networked standby power (Pnet) for CLS, expressed in W and rounded to the second decimal	:	0.00	Colour rendering index, rounded to the nearest integer, or the range of CRI values that can be set
Outer dimensions without separate control gear, lighting control parts and non-lighting control parts if any (mm)	:	Height: 48 Width: 220 Depth: 220	Spectral power distribution in the range 250nm to 800 nm at full-load
Claim of equivalent power	:	-	If yes, equivalent power (W)
			Chromaticity coordinates (x and y)
			0.440, 0.403
Parameters for directional light sources			
Peak luminous intensity (cd)	:	-	Beam angle in degrees, or the range of beam angles that can be set
Parameters for LED and OLED light sources			
R9 colour rendering index value	:	10	Survival factor
the lumen maintenance factor	:	0.96	
Parameters for LED and OLED mains light sources			
displacement factor	:	0.95	Colour consistency in McAdam ellipses
Claims that an LED light source replaces a fluorescent light source without integrated ballast of a particular wattage	:	-	If yes then replacement claim (W)
Flicker metric (Pst LM)	:	0.2	Stroboscopic effect metric (SVM)
			0.1

Declared/Measured values			
Voltage (V)	: 230	Useful luminous flux (lm)	: 1450 in sphere
Frequency (Hz)	: 50	Luminance-HLLS (cd/mm ²)	: - HLLS
On-mode power Pon (W)	: 15.0	Beam angle (°)	: - DLS
Standby power Psb (W)	: 0.00	Networked standby power Pnet (W)	: 0.00 CLS
Displacement factor	: 0.95	CCT(K)	: 3000
Colour consistency (SDCM)	: 6	CRI	: 80
Flicker metric PstLM	: 0.2	Stroboscopic effect metric SVM	: 0.1
Ponmax (W)	: 15.1	excitation purity for Blue 440nm-490nm	: - CTLS
Total mains efficacy (lm/W)	: 100	excitation purity for Green 520nm-570nm	: - CTLS
LB0750(H)	: 15000	excitation purity for Red 610nm-670nm	: - CTLS
Parameters for separate control gear			
Voltage (V)	: -	Maximum output power (W)	: -
No-load power Pno (W)	: -	Efficiency in full load (%)	: -
Standby power Psb (W)	: -	Networked standby power Pnet (W)	: -
the type of light sources for which it is intended	: -	compatible dimmable light sources	: -
Outer dimensions (mm)	Hight	mass(g)	: -
	Width		
	Depth		
$\eta_{TM} = (\Phi_{use}/P_{on}) \times FTM \text{ (lm/W)} = 100 \text{ lm/W}$ $85 \leq \eta_{TM} < 110$ energy efficiency class correspond to F			
Energy efficiency and functional requirements			
Classification acc. To 2019/2020	<input type="checkbox"/>	Directional lamp	<input checked="" type="checkbox"/> Non directional lamp
Compliance:	<input checked="" type="checkbox"/>	Yes	<input type="checkbox"/> No
Measurement conditions			
Standards	:	EU 2019/2015, EU 2019/2020	
Tolerances	:	according to ErP regulation	
Measurement setup	:	4P, SSL port, 1.5m spere	
Voltage (V)	:	declared voltage	
Burning position	:	Base up	
Ambient temperature:	:	25°C +/- 2K	
Burn in	:	1h	
Total operating time during measurement	:	15min	
Non standard stability criteria	:	Luminous flux tolerance 0.5% within 60 sec.	
Uncertainties	:	according to JCGM (GUM) and CIE 198	
Important notes / WARNINGS:			
The product needs to be powered off before install; Please see users' instruction			
Signature	:	Vick Xun	